

RT21 Hand transmitter

The RT21 hand transmitter is available in a 1-channel or 2-channel version.

Above all, it is used to control electrical gate mechanisms or as a paging device.

An easily visible LED lights up when the battery needs to be changed.



RT21E5001-01-23K

RT21E5002-01-23K

Technical specifications

Coding	factory coding with Easywave Telegram
Frequency	868.30 MHz
Channels	1 or 2
Range	typically 150 m in good free-field conditions
Power supply	1x 3V battery, CR2032
Operating indicator	LED
Operation	transmission lasts as long as the button is pressed (maximum 36 seconds)
Function	depends on the receiver (see Models)
Operating temperature	-20 °C to +60 °C
Dimensions	36 x 55 x 16 mm
Weight	35 g (including battery)
Color	anthracite gray similar to RAL 7016

Scope of delivery

- Hand transmitter including battery
- Operating manual

Models

Product numbers	Description	Function
RT21E5001-01-23K	Hand transmitter 1-channel, anthracite gray, red button	1x PULSE
RT21E5002-01-23K	Hand transmitter 2-channel, anthracite gray, gray button	1x ON/OFF